






Contents

Overview of MyHOME_Screen	5
Scrolling	5
Writing	6
Reorganising objects inside a page	7
Pushbuttons and connections	8
Status icons	9
Answering a video door entry call	10
Alarm notification	10
Receiving a message from the switchboard	10
Profiles	11
Rooms	12
Functions	15
Multimedia	16
Devices	16
Web browser	17
IP radio	17
Webcam, Weather, Web links, Rss	18
Settings	19
Settings > Home	19
Home page skin	19
Change background image	19
Restore background image	19
Quicklinks	20
Settings > General	21
Info	21
Date and time	21
Network	21
Display	21
International	21
Password	21
Beep	21
Settings > Profiles	22
Settings > Rooms	22
Settings > Functions	23
Scenarios > Scenario Module	23
Scenarios > MyHOME_Screen scenario	23
Energy	24
Video door entry	24
Settings > Alarm clock	25
Settings > Multimedia	27

Add Quicklink	27
Browser	27
Settings > Ringtones	27
Control your My Home system	28
Lighting	28
Automation	30
Temperature control	32
Video door entry	40
Sound system	41
Antintrusion	43
Messages	44
Energy management	45
Scenarios	50

Overview of MyHOME_Screen



1. Status bar with [Status icons](#).
2. Quick access [Pushbuttons](#).
3. Access to the [Rooms](#), [Functions](#), [Settings](#), [Multimedia](#) pages.
4. [Quicklinks](#).
5. Access to [Profiles](#).

Scrolling

Touch and drag left or right to scroll. In addition to using your finger, you can also scroll by touching the arrows, « and ».

For some pages, like the web pages, the screen can also be scrolled up or down. When scrolling using your finger the content of the screen is displayed but no functions are activated.



Writing

The screen keyboard appears automatically each time text needs to be entered.



- Capital letters: touch followed by the letter.
- Activate Capital block: to keep typing in capital letters, touch twice in succession.
- Numbers, punctuation marks, or symbols: touch . To see other punctuation marks and symbols, touch .
- Accents and other alternative characters: touch and hold your finger on a key, and touch to select an option.







- Hide the keyboard: touch .
- Delete text: touch .




To correct mistakes move the cursor to the desired word using the and arrows.


To change the language of the MyHOME_Screen keyboard see [International](#).

Reorganising objects inside a page


You can change the position of items as you like by dragging them around the screen. Touch and hold any item/link until a black area appears, and the icons in vertical sequence at the side of the link **T**   .



- To change the name of the item/link touch **T** (see [Writing](#)).
- To change the URL and the name of a link touch .
- To remove the item/link touch .
- To move an item/link touch , and then touch any point in the dark area.
















Pushbuttons and connections



1. Secure Digital memory card connector.
2. USB-miniUSB connector for the connection of MyHOME_Screen to the PC.
3. USB connector for USB PenDrive.
4. Call answering pushbutton.
5. Door lock release pushbutton.
6. Cameras ON and cycling pushbutton.
7. Standby/reactivate pushbutton.

Status icons


Icon		Meaning
	Alarm clock ON	One or more alarm clocks are enabled. Touch the icon to modify the alarm clock settings (see Settings > Alarm clock).
	Burglar alarm OFF	The burglar alarm is disabled. Touch the icon to modify the burglar alarm settings (see Antintrusion).
	Burglar alarm ON	The burglar alarm is enabled. Touch the icon to modify the burglar alarm settings (see Antintrusion).
	Sound ON	MyHOME_Screen sound is enabled.
	Sound OFF	MyHOME_Screen sound is disabled.
	Multimedia reader ON	A music track is being played. Touch the icon to display the multimedia player (see Multimedia).
	Alarm in memory	A system alarm has occurred. Touch the icon to view the alarm details (see Antintrusion).
	Stop&Go open	The Stop&Go is open. Touch the icon to access the Stop&Go details page: it is possible to force rearming if the device allows it. (see SYSTEM SUPERVISION).
	Incoming message (from the switchboard).	One or more messages have been received from the switchboard. Touch the icon to read the messages (see Messages).
	Professional studio function ON	When a video door entry call is received the associated door lock will open automatically. Touch the icon to disable the function from the settings screen Video door entry .
	Call exclusion	No sound will be emitted by MyHOME_Screen on receipt of a call. Touch the icon to disable the function from the settings screen Video door entry .
	Handsfree function ON	When a video door entry call is received MyHOME_Screen will answer automatically without the need to touch any keys. Touch the icon to disable the function from the settings screen Video door entry .
	Home icon, to return to the main screen	
20.5 °C	Temperature measured inside the zone set by the software	

Answering a video door entry call





MyHOME_Screen receives a call from the entrance panel while in standby.
The centre of the display shows the image recorded at the entrance panel.


Touch  to answer the call, or press the # pushbutton at the side of MyHOME_Screen (see [Pushbuttons and connections](#)).


Touch  to reject or end the call.

Touch  to open the door lock, or press the ○= pushbutton at the side of MyHOME_Screen (see [Pushbuttons and connections](#)).


To switch the staircase light ON (if installed in your system), touch .

Use the  and  icons to decrease or increase the volume of the loudspeaker; press the  icon to switch OFF the microphone of MyHOME_Screen, changing the status of .

Touch  to display the tools for adjusting the image shown on the display during the video door entry call:




Use icons  and  to adjust brightness, contrast and colour.


Touch  to cycle the cameras of the system or press the ○ pushbutton at the side of MyHOME_Screen (see [Pushbuttons and connections](#)).


Alarm notification

MyHOME_Screen receives an alarm notification while in standby.

The alarm message, with the time, date, type, and zone where the alarm has occurred, appears at the centre of the display.


Touch  to see the alarm details (see [Antintrusion](#)).

Touch  to ignore the alarm and display it later.


When an alarm is ignored, the status bar shows the  icon. Touch this icon to see the alarm details (see [Antintrusion](#)).

Receiving a message from the switchboard

MyHOME_Screen receives a message from the switchboard while in standby.

Touch  to see the message details (see [Messages](#)).

Touch  to ignore the message and display it later.

When a message is ignored, the status bar shows the  icon. Touch this icon to see the message details (see [Messages](#)).

Profiles

Use the profiles to make the most of your MyHOME_Screen.

Inside the profile you can recall the most used functions with a simple touch

You can also enter customised notes.

Touch the [profile card](#) previously created using the software in the Home page.



1. Touch to return to the Home page.
2. Touch to customise the profile previously created by the software (see [Settings > Profiles](#)).
3. Touch to perform the function in the profile.
4. Touch to add a note to the profile.
5. Touch to customise the profile previously created by the software (see [Settings > Profiles](#)).


Rooms

Using Rooms, simply touch the card of a room to access its functions.


You can recall the functions enabled for the room with a simple touch.

Each card displayed belongs to a room of your home (e.e. living room, bathroom, kitchen, etc...).

Touch [Rooms](#) in the Home page.



1. Touch the floor where the room is located (if available).



2. Touch the card of the room to display.






3. Touch to return to the room list page.
4. Touch to customise the room you are in (see [Settings > Rooms](#)).
5. Touch to return to the room list page.
6. Touch to execute the function in the profile (see [Control your My Home system](#)).



CUSTOMISATION OF DESCRIPTIONS AND MOVING ITEMS

MyHOME_Screen gives the possibility of customising the descriptions of the functions entered, and the position of the items inside the page.




1. Touch the item that you want to customise for a few seconds.
 - To change the name of the item/link touch . The keyboard appears, so that the desired customisation can be entered (see [Writing](#)).
 - To move an item/link touch , and then touch any point in the dark area.

Functions

Using Functions, simply touch the system card to access its functions.

Each card displayed belongs to a system of the installation (e.g. automation, lights, temperature control, etc...).

Touch [Functions](#) in the Home page.



1. Touch the card of a system to access its functions ([Control your My Home system](#)).
2. Touch to return to the Home page.

Multimedia





From the Multimedia page it is possible to access the USB and SD ports. These can be used to connect devices containing music or images, which can then be played using MyHOME_Screen. The My Media Server function gives you the possibility of displaying the multimedia contents found on all the PCs connected to the same network of MyHOME_Screen. Lastly, you can access Web contents, like Web Radio, Rss, Web Browser, and Webcam.


Devices

Touch [Multimedia](#) in the Home page and then touch the card *Devices*.

Select *USB* To display and use the content of your USB key.


MyHOME_Screen will be able to play any music, videos and images.



Icons , , ,  give you the possibility to filter your USB key, distinguishing between documents, music, videos, and images.


Before disconnecting the USB key touch .

PLAYING AN AUDIO FILE



To play an audio file (MyHOME_Screen can only play mp3 files) touch the name of the track.





Touch  to go to the previous track, and  to go to the next track. Hold the finger on these two icons to fast forward or rewind the track.

Touch  to pause or play the track.

Touch  to stop playback of the track; MyHOME_Screen will automatically switch to the Multimedia page.

Touch  to return to the selection of the files without stopping playback of the track. You can return at any time to the track being played by touching the  icon in the status bar (see [Status icons](#)).

Use icons  and  to decrease and increase the volume.


Touch  to disable the volume; the icon changes status (.



PLAYING A VIDEO FILE



To play a video file (MyHOME_Screen can only play mp4 files), touch the name of the video.



Touch  to go to the previous video and  to go to the next video.

Touch  to pause or play the video.

Touch  to disable the volume; the icon changes status (.

Use icons  and  to decrease and increase the volume.



Touch  to return to the selection of the file.



IMAGE PLAYBACK


To open an image (MyHOME_Screen can only open .jpg or .png images), touch the name of the image.



Touch  to go to the previous image, and  to go to the next image.


Touch  to start or pause the image slide show.

The  and  icons can be used to decrease and increase the time each image will be displayed (minimum 8 seconds, maximum 50 seconds).

Touch  to return to the selection of the file.

Web browser

Touch [Multimedia](#) in the Home page and then touch the card *Web browser*.



To display a web page touch the address field (in the title bar), enter the URL, and touch .

Scroll the web page moving your finger up, down, or sideways.

To reload a web page touch .

To close a web page touch .

Touch and to go to the previous page, or to the next one.

Touch and then or to zoom in or out of the web page; touch to bring the size back to 100%.

IP radio

Touch [Multimedia](#) in the Home page and then touch the *IP Radio* card.

The list of IP Radio channels saved appears touch one to start broadcasting.



Touch to go to the previous radio channel and to go to the next radio channel.

Touch to mute the radio, or start broadcasting.

Touch to stop radio broadcasting; MyHOME_Screen will automatically switch to the Multimedia page.

Touch to return to the list of IP Radios.

Use icons and to decrease and increase the volume.

Touch to disable the volume; the icon changes status ().


Webcam, Weather, Web links, Rss

Touch [Multimedia](#) in the Home page and then one of the following cards *Webcam*, *Weather*, *Web links*, *Rss*.

The functions "Webcam", "Weather", "Web links", and "RSS" give you the possibility of displaying or listening to Web contents. In order for this application to be enabled, the device must be connected to a LAN network with ADSL service.



Warning: the help file only explains the "Webcam" function because MyHOME_Screen manages also the "Weather", "Web links", and "Rss" functions in the same way.



1. Touch a webcam of the list to display it on the Web.
2. Touch to return to the Multimedia page.



Settings

Use the [Settings](#) menu to access a range of advanced MyHOME_Screen settings and parameters.

[Settings > Home](#)

[Settings > General](#)

[Settings > Profiles](#)

[Settings > Rooms](#)

[Settings > Functions](#)

[Settings > Alarm clock](#)

[Settings > Multimedia](#)

[Settings > Ringtones](#)

Settings > Home

Home page skin

To change the skin of MyHOME_Screen, touch *Settings > Home > Home page skin* and select either the *Light* or the *Dark* skin.





Warning: after selecting the desired language do not touch the MyHOME_Screen display until this has restarted

Change background image

To change the background image of MyHOME_Screen, touch *Settings > Home > Change background image*.

You can select the image from *Images* (the images pre-loaded in MyHOME_Screen will be suggested), *Last Used* (the already previously used images will be suggested), *USB* (if a USB key is connected to the corresponding port), *SD* (if a SD card is connected to the corresponding port), or *My MediaServer* (if one or more PCs are connected to the LAN network, with file and folder sharing enabled).

Restore background image

To restore the original MyHOME_Screen background image touch *Settings > Home > Restore background image* and then touch  to confirm or  to abort.

Quicklinks

To add a link to the Home screen (maximum 7) touch *Settings > Home > Quicklinks* and then *Add Quicklink*.

Connections to cameras/entrance panels and scenarios can be selected among the ones available (the same that you find in the Functions page).

For connections to Web Page, Webcam, Rss, Weather, and Web Radio:

1. Touch *Web page*.
2. Enter the URL of the web page.
3. Enter a customised description to be associated to the web page.
4. Touch *ADD* to add the created link to the list of links.

5. Touch the created link to select it (after selection this can also be deleted by touching).
6. Touch *OK* to confirm or *CANCEL* to abort.



Warning: the procedure to add links to Web Page, Webcam, Rss, Weather, and Web Radio is the same.



Settings > General



Info



To display MyHOME_Screen configuration/address information touch *Settings > General > Info*.

Date and time

To change the date and the time of MyHOME_Screen touch *Settings > General > Date and time*.

Use  and  to set the day, the month, and the year;

use  and  to set the hours and the minutes;

after completing the modification, touch  to confirm, or  to abort.

Network

To display and edit some MyHOME_Screen network parameters touch *Settings > General > Network*.

To connect MyHOME_Screen to the network touch *Network status* and *Connect*; to disconnect touch *Disconnect*.

Depending on your network parameters, touch *IP configuration* and select *DHCP* or *Indirizzo IP Static IP address*.



After completing the modifications, touch  to confirm, or  to abort.




Warning: after selecting the desired language do not touch the MyHOME_Screen display until this has restarted

Display

To modify the MyHOME_Screen display parameters touch *Settings > General > Display*.

To change the brightness touch *Brightness*; use  and  to decrease or increase the brightness of the display.

To adapt MyHOME_Screen to your touch, touch *Calibration* and then the **X** icon until , appears, which must then be touched twice.

To clean the display touch *Clean*, MyHOME_Screen will go in stand-by for 10 seconds. The countdown will be shown on the display.

Note: The LCD screen has been manufactured using high precision advanced technology. It is however possible to continually have up to 5 small black and/or luminous points (red, blue, green) on the LCD screen. This is a normal result of the manufacturing process, and does not indicate wrong and/or defective operation.

International

To change the MyHOME_Screen and the keyboard language touch *Settings > General > International*.

Touch *Text language* to select the device language; touch *Keyboard language* to select the language of the keyboard of the device.





Warning: after selecting the desired language do not touch the MyHOME_Screen display until this has restarted.

Password



To change the password touch *Settings > General > Password*.

Touch *Change Password* a window will appear, for entering the current password (default 1234567), the new password select, and the new password again, to confirm.

After completing the password modification, touch  to confirm, or  to abort.

Touch *Disable* to disable the password request, or *Enable* to enable it.

Beep

To set the sound mode every time the MyHOME_Screen display is touched, touch *Settings > General > Beep* and touch  to enable, or  to disable.

Settings > Profiles

To display and customise all the profiles previously created by the software touch *Settings > Profiles*.



Touch a profile to customise it according to your needs.

To modify the image of the card touch *Change card image*.

You can select the image from *Images* (the images pre-loaded in MyHOME_Screen will be suggested), *Last Used* (the already previously used images will be suggested), *USB* (if a USB key is connected to the corresponding port), *SD* (if a SD card is connected to the corresponding port), or *My MediaServer* (if one or more PCs are connected to the LAN network, with file and folder sharing enabled).

To change the background image of the profile, touch *Change background image* (see [Change background image](#)).

To add a link on the main screen of the profile touch *Add Quicklink* (see [Quicklinks](#)).

To restore the original MyHOME_Screen background image touch *Restore background image* and then touch  to confirm or  to abort.

Settings > Rooms

To display and customise the rooms of your home touch *Settings > Rooms*.

Touch the floor the room belongs to (if applicable), and then the room to customise.


To change the card image touch *Change card image* (see [Settings > Profiles](#)).

To change the background image of the room, touch *Change background image* (see [Change background image](#)).

Settings > Functions

Scenarios > Scenario Module


Touch **Settings > Functions > Scenarios** and then **Scenario module > Start programming** to access the scenario modification or creation procedure.



1. Touch to start the procedure for the creation of the scenario and then use the controls/actuators of your system to modify the existing scenario. After operating the controls/actuators, touch **Ok** to save the scenario.



*To create a new scenario you must first delete the existing one.
Touch **Scenario Module > Delete the Scenario** followed by **Ok** o confirm.
To create a new scenario follow the above procedure.*




2. Touch **Ok** to confirm or **Cancel** to abort.

To activate the Scenario of the Scenario Module (see [SCENARIO MODULE](#))

Scenarios > MyHOME_Screen scenario

Touch **Settings > Functions > Scenarios** followed by **MyHOME_Screen Scenario** to access the procedure for the creation of MyHOME_Screen scenarios.





1. Touch to change the time condition of the scenario, selecting the day or days.
2. Touch to change the time condition of the scenario, selecting the time the event shall occur.
3. Touch **OK** to confirm or **CANCEL** to abort.





To activate and enable the MyHOME_Screen Scenario (see [MyHOME_Screen SCENARIO](#))

Energy

Touch **Settings > Functions > Energy** to customise the energy parameter based on your need.


To set a tariff for each measured item (electricity, gas, etc.), touch **Tariffs** and then the item; use  and  to decrease or increase the tariff;

touch  to confirm or  to abort.


It is possible to enter the monthly consumption goals for each meter. To do this touch **Consumption goals**; MyHOME_Screen will notify when these goals have been reached/exceeded. Select the row where to enter your consumption goal; touch  to enable (when enabled the  icon is displayed) the goals. Then set the goal for each month, decreasing/increasing using icons  and .

Touch  to confirm or  to abort.



It is also possible to enter and enable one, or maximum two instantaneous consumption thresholds for each meter. To do this touch **Thresholds**, MyHOME_Screen will notify when these thresholds are exceeded; select the row where to set the threshold.





Touch  to enable (if enabled, the  icon is displayed) an alarm when the threshold is exceeded. To change the thresholds touch .







Use icons  and  to decrease and increase the threshold.

Touch  to confirm or  to abort.

Video door entry

If the function **Handsfree**, is enabled, when a video door entry call is received, MyHOME_Screen answers automatically without the need to touch any keys; touch  to enable the function, or  to disable it.


If the function **Professional studio**, is enabled, when a video door entry call is received, the door lock associated is automatically released, without the need to touch any keys; touch  to enable the function, or  to disable it.

If the function **Ringtone exclusion**, is enabled, no sound is emitted by MyHOME_Screen when a video door entry call is received; touch  to enable the function, or  to disable it.


You can associate a Teleloop device to MyHOME_Screen by touching .

Settings > Alarm clock

To add an alarm clock touch *Settings*> *Alarm clock* and then *Add alarm clock*. The alarm clock is added to the list. Touch it to change its settings.







Touch to enable; if enabled the icon is displayed. In *Repetition* touch to set/change the alarm clock parameters:








1. Select the days when the alarm clock should go off, or if it should go off only once.
2. Use and to set the alarm clock time.
3. Enter a customised description to be associated to the alarm clock.
4. Touch to confirm or to abort.


In *Ringtone* touch  to select the type of alarm clock to use:



5. Select *Beep* To use MyHOME_Screen as alarm clock, or *Sound system* to switch a sound system amplifier ON.
6. Use  and  to set the alarm clock volume.
7. Select the source to use for the alarm clock.
8. Touch  to activate the selection of the rooms.



9. Use  and  to select the room where the alarm clock will go off.
10. Touch  to return to the selection of the sources.
11. Touch to select which amplifier will be activated by the alarm clock.
12. Touch  to confirm or  to abort.

Touch  to remove the alarm clock.





Settings > Multimedia

Add Quicklink





To customise the web content links (*Rss*, *Rss Weather*, *Web radio*, *Webcam*, *Web Links*), that it will be possible to recall from the multimedia pages, the profiles, and the home page, touch *Settings > Multimedia > Add quicklink* followed by the type of link to add/edit(see [Quicklinks](#)).

Browser

To customise the browser touch *Settings > Multimedia > Browser*.

Touch *Change Home Page* to change the page that will be displayed when the web browser opens; touch *Enable history* and then touch  to save the browser history, or  to disable saving; touch *Clear history* followed by  to delete the browser history, or  to abort.

Settings > Ringtones

To set a dedicated ringtone for each type of call, message, alarm, etc., touch *Settings > Ringtones*. Select the option to associate the ringtone to (e.g. *Message Ringtone*) and then use icons  and  to select the ringtone to associate among the ones available; use  and  to decrease or increase the ringtone volume.

Control your My Home system


Lighting

You can switch a light or a group of lights ON or OFF, adjust their intensity, as well as set the lights to come on for set times.

Touch [Functions](#) in the Home page, and then touch the *Lighting* card.

SINGLE LIGHT / TIMED LIGHT AT SET TIMES

This control can be used to switch a single light ON or OFF. It also gives the possibility to set the time the light stays on.



Use the **ON** and **OFF** icons to switch the light ON or OFF.

Touch **<** and **>** to set the ON time (1, 2, 3, 4, 5, 15 min. / 0.5, 30 sec.).

GROUP OF LIGHTS


This control can be used to simultaneously switch ON or OFF a group of lights and dimmers.



Use the **ON** and **OFF** icons to switch the light ON or OFF.

FIXED TIMED LIGHT

This control can be used to switch a light ON for the time set using the configuration software (which can be changed directly from MyHOME_Screen).



Use the **ON** and **OFF** icons to switch the light ON or OFF.

Touch **< O** to enable the ON time; if enabled, the **I >** icon is displayed.

Use **+** and **-** to set hour, minutes and seconds.

STAIR LIGHT


This control can be used to activate the video door entry Stair Light function.



Use the **ON** and **OFF** icons to switch the stair light ON or OFF.

10 LEVEL DIMMER/100 LEVEL DIMMER


This control can be used to switch a dimmer ON or OFF, and to adjust its intensity. With a 10 level dimmer 10 levels of adjustment are possible, while with a 100 level dimmer 100 levels of adjustments are possible.




Use the **ON** and **OFF** icons to switch the light ON or OFF.
 Touch **-** and **+** to adjust the dimmer intensity.
 Touch **<** e **>** to set the ON time (1, 2, 3, 4, 5, 15 min. / 0.5, 30 sec.).

CUSTOMISATION OF DESCRIPTIONS

With MyHOME_Screen it is possible to customise the descriptions of the functions.



1. Touch the description that you wish to customise for a few seconds.



2. The keyboard appears, so that the desired customisation can be entered (see [Writing](#)).













Automation

It is possible to manage in a simple way all the automatisms of your My Home system, like rolling shutters, shutters, motorized curtains, controlled sockets, watering system, etc.

Touch [Functions](#) in the Home page and then touch the *Automation* card.

OPEN/CLOSE and UP/DOWN CONTROLS

These controls can be used to open and close curtains, shutters, etc. with a simple touch. Based on the programming of the installer, operation can be in two different ways:

- normal mode:
the opening and closing movement is performed while the corresponding icon is touched ( /  or  / ), The icon changes status to confirm the movement ( or ).
When the icon is released, movement will stop automatically.
- modalità normale:
The opening or closing movement starts when the corresponding icon is touched ( /  or  / ); during movement the icon changes status, showing the  icon; to stop the movement touch the  icon.

Examples of safe mode





1. While the icon is pressed the automatic device opens; when the finger is removed it stops.





2. While the icon is pressed the automatic device moves down; when the finger is removed it stops.

Examples of normal mode



3. Touch the icon to activate the opening of the device; touch  icon to stop it.



4. Touch the icon to activate the opening of the device; touch  icon to stop it.

AUTOMATION GROUP

This control can be used to activate several (2 statuses) automatisms at the same time. For example, a single touch will switch ON or OFF all the fans inside the house.



The movement is activated by touching , and stopped by touching .

ON CONTROL

This control works as a pushbutton: the door lock is activated while the icon is pressed, and is deactivated when the icon is released. If controlling the video door entry system door lock, the activation time is set during the configuration of the door lock.







Touch  to activate the electrical door lock.

ON/OFF CONTROL

This control can be used to switch and automatism (e.g. fan, watering system, etc.) ON or OFF.



Touch  to switch the automatism ON (the status of the icon changes to ); to switch it off touch  (the status of the icon changes to .

CONTACT

This control provides a synchronised view of the status of a contact connected to the system.



The active icon shows the status of the contact:

 = contact open.

 = contact closed.

OPEN/CLOSE GROUP

This control can be used to activate several (3 statuses) OPEN/CLOSE automatisms at the same time. For example, a single touch will open or close all the shutters of the home.



CUSTOMISATION OF DESCRIPTIONS

MyHOME_Screen can be used to customise the descriptions of the functions (see [CUSTOMISATION OF DESCRIPTIONS](#)).

Temperature control

It is possible to control and regulate the heating or the air conditioning system using the zone controls, based on personal current needs.


Touch [Functions](#) in the home page and then touch the *Temperature control* card.

The list of the systems, the non controlled zones (if present), the external probes(if present), and the air conditioning system (if present) is displayed.




Warning: The management of the temperature control system is only possible if the Remote Control function is active on the central unit.

TEMPERATURE CONTROL CENTRAL UNIT




1. Touch to display your temperature control system.
2. Touch to display the status of the central unit.
3. Touch to select the operating mode of the central unit.
This operation is used to set the operating mode of the system:
Summer = cooling;
Winter = heating.



4. Touch to select the operating mode of the central unit.
You can select the operating mode of your system: for example, you can select one of the weekly programs, or set a fixed temperature for all the zones.

Weekly Mode


This mode can be used to operate your system in automatic mode, following the program set on the central unit; depending on your requirements, the programs set in the central unit can change the temperature during the 24 hours, for each day of the week.



Weekday Mode


This mode can be used to select a specific daily profile for a set period.

The program is performed until the set date and time, after which the selected weekly program will be activated.



Holiday Mode

This mode can be used to maintain (during extended absence, for example during holidays), the system in Antifreeze or Thermal Protection mode, until the set date and time, after which the selected weekly program will be activated.




Antifreeze or Thermal Protection mode

You can decide to have one or more zones, or even the whole system, in antifreeze mode (or thermal protection mode during the summer months).

In Antifreeze mode, a minimum temperature of 7°C is ensured.

In Thermal Protection, a maximum temperature of 35°C is ensured.



Manual Mode

This mode can be used to set a constant temperature in all the zones of your system.

Manual Mode screen showing the following options:

- CENTRALE
- Season: Winter
- Manual Mode
- Temperature set: 21.5°C (with minus and plus buttons)
- Ok and Cancel buttons

OFF Mode

This mode can be used to switch OFF all the zone of your system.

OFF Mode screen showing the following options:

- CENTRAL UNIT
- Season: Winter
- Mode: Off
- Ok and Cancel buttons

Scenario Mode

This mode can be used to select one of the 16 summer scenarios or one of the 16 winter scenarios; your system will operate automatically following the scenario set.

Scenario Mode screen showing the following options:

- CENTRAL UNIT
- Season: Winter
- Scenario Mode
- Next scenario: Winter 1 (with minus and plus buttons)
- Ok and Cancel buttons

Timed Mode (4 zone central unit)


This mode can be used to operate the system in manual mode in all the zones for a set time.

Timed Mode screen showing the following options:

- CENTRAL UNIT
- 22.8°C
- Season: Winter
- Timed manual mode
- Time: 10:30 (with edit icon)
- Temperature set: 19.00°C (with minus and plus buttons)
- Ok and Cancel buttons

ZONES (99 ZONE CENTRAL UNIT)


For each zone, the zone name, the temperature measured, the operating mode, and the status of the probe (-3, -2, -1, 0, +1, +2, +3) are displayed.



1. Touch to display the details of the zone.
2. Touch to select the operating mode of the zone.

ZONES WITH FAN-COIL FUNCTION (99 ZONE CENTRAL UNIT)

For each zone, the zone name, the temperature measured, the operating mode, the status of the probe(-3, -2, -1, 0, +1, +2, +3), and the speed of the fan-coil are displayed.



1. Touch to display the details of the zone.
2. Touch to set the speed of the fan-coil.

THERMAL PROBE

The local offset of the probe is the adjustment of the knob of the probe found in each zone of your temperature control system.

If the probe is in the ✖ position (antifreeze/thermal protection) or in the OFF position, no adjustment will be possible using MyHOME_Screen. In this case, the settings can only be changed using the probe knob.

ZONES (4 ZONE CENTRAL UNIT)


For each zone, the zone name, the temperature measured, and the status of the probe(-3, -2, -1, 0, +1, +2, +3) are displayed.



1. Touch to display the temperature measured.

ZONES WITH FAN-COIL FUNCTION (4 ZONE CENTRAL UNIT)


For each zone, the zone name, the temperature measured, the status of the probe(-3, -2, -1, 0, +1, +2, +3), and the speed of the fan-coil are displayed.



1. Touch to display the details of the zone.
2. Touch to set the speed of the fan-coil.


EXTERNA PROBES

In case of external radio probes installed in the system, the temperature measured by them can be displayed.




NON CONTROLLED ZONES (4 AND 99 ZONES)

If the system includes probes for the measurement of the temperature only (non controlled zones), it is possible to display the temperature measured by them.



BASIC AIR CONDITIONING


Air conditioning in basic mode gives you the possibility of managing the splitters of the system using commands previously entered by the software. If a temperature probe has been associated to the splitter, MyHOME_Screen will be able to display the temperature detected in the corresponding room.



1. Touch to display your air conditioning system.
2. Touch the splitter to control.
3. Touch to select the program.
4. Select the program to be performed on the splitter.

ADVANCED AIR CONDITIONING


Use the advanced mode to manage the splitter as if you were using its remote control.



1. Touch to display your air conditioning system.
2. Touch the splitter to control.
3. Touch to select the operating mode of the splitter.
4. Select the splitter mode.

OFF Mode

This mode is used to switch the splitter OFF.



Heating Mode

LIVING ROOM

Program

>

Heating Mode

>

Temperature

19.00°C

-

+

Fancoil

Auto

<

>

Swing

Off

<

>

Ok

Cancel

Cooling Mode

LIVING ROOM

Program

>

Cooling Mode

>

Temperature

19.00°C

-

+

Fancoil

Auto

<

>

Swing

Off

<

>

Ok

Cancel

Fan Mode

LIVING ROOM

Program

>

Fancoil Mode

>

Fancoil

Auto

<

>

Swing

Off

<

>

Ok

Cancel

Dehumidifier Mode

LIVING ROOM

Program

>

Dehumidifier Mode

>

Swing

Off

<

>

Ok

Cancel

Automatic Mode

LIVING ROOM	
Program	>
Automatic Mode	>
Temperature	
19.00°C	- +
Fancoil	
Auto	< >
Swing	
Off	< >
Ok	Cancel



Warning: The control functions depend on the type of splitter installed on the system and the software configuration.

Group controls

AIR CONDITIONING	
Kitchen	>
Living room	>
Group of controls	>

Video door entry

Depending on your video door entry system, you can control the door lock release or the staircase light for each entrance panel, communicate with internal units or with an associated switchboard, or display the system cameras.

Touch [Functions](#) in the Home page and then touch the *Video Door Entry*.card.

VIDEO CONTROL

This can be used to monitor your home by activating one of the cameras inside the apartment or in the common areas.

Touch a camera.

The screen shows the image of the selected camera.



Warning: if the audio/video channel is occupied by another user the command is not performed. Wait for the channel to be free and try again.

If a call is received from the entrance panel, the connection will be interrupted.

For further information on the operation of the corresponding see [Answering a video door entry call](#).

INTERCOM

This can be used to talk to other video/audio internal units installed in your home, or in other apartments.


Select the type of call and .

MyHOME_Screen calls the associated internal unit.







Warning: if the audio/video channel is occupied by another user the command is not performed. Wait for the channel to be free and try again.

If a call is received from the entrance panel, the conversation will be interrupted.



Touch  to end the call.

Use the  and  icons to decrease or increase the volume of the loudspeaker; press the  icon to switch OFF the microphone of MyHOME_Screen, changing the status of .


Sound system

You can control and manage your My Home sound system.

Touch [Functions](#) in the home page and then touch the **Sound system** card.

MUSIC SOURCE

You can choose the radio tuner, an external source (Aux), like for example a CD player (controlled through the Stereo Control, or connected to the RCA input), MyHOME_Screen used as multimedia source, or an external source (USB or SD), and the Media Server function.



1. Touch to select the source.

TUNE THE RADIO


MyHOME_Screen gives you the possibility of tuning the radio of your sound system.



1. Touch to manually change the frequency.
2. Touch to switch to another saved frequency.

AMPLIFIER


This control can be used to switch the amplifier ON or OFF, or to adjust the volume.



1. Use the **ON** and **OFF** icons to switch the amplifier ON and OFF.
2. Use the **+** and **-** to decrease and increase the volume.

GENERAL


This control can be used to switch all the amplifiers of the system ON or OFF, and to adjust their volume.




1. Use the **+** and **-** to decrease and increase the volume.
2. Use the **ON** and **OFF** icons to switch the amplifiers ON and OFF.

POWER AMPLIFIER


This control can be used to switch ON or OFF the power amplifier and to manage it.



1. Use the **ON** e **OFF** icons to switch the power amplifier ON and OFF.
2. Use the **+** e **-** to decrease and increase the volume of the power amplifier.
3. Touch to open the power amplifier management menu.



4. To adjust the treble level from -10 to +10 use icons **<** and **>**.
5. To adjust the bass level from -10 to +10 use icons **<** and **>**.
6. adjust the balance from -10 to +10 use icons **<** and **>**.
7. Touch to select the equaliser curve.




8. The activation of Loud mode enhances bass and treble frequencies when listening at low volume. Touch to enable or disable Loud mode.



Antintrusion

You can control and manage the status of the burglar alarm system.

Touch [Functions](#) in the home page and then touch the *Antintrusion* card.



1. ENABLE/DISABLE THE BURGLAR ALARM

To enable the system touch to disable the system touch .

In both cases enter your user code for the burglar alarm central unit.

If the wrong code is entered appears, otherwise the screen will show . If the sound system is enabled on the burglar alarm central unit, the message, "enabled"/"disabled" will be heard.

The icons indicate the status of the zones; in the examples, zones 1, 2, 4 and 5 are enabled/included, while zones 3, 6, 7 and 8 are disabled/excluded.

Enable/Disable the zones

With the whole burglar alarm is disabled () it is possible to disable or re-enable one or more zones of the system. This gives you the possibility of customising the operation of the system following your specific needs.

For example, you can exclude the infrared sensor zones, leaving the perimeter zones active (entrance door and windows), so that you can move freely around your home whilst preserving your safety.

This customisation is only possible when the system is disabled, and is performed using the icons of the individual zones.

To separate the zones, touch the zones to enable, followed by ; you will be asked to enter the code. Once the code has been entered, touch to enable the system. You will be asked to re-enter the code.

2. SCENARIO

Touch a scenario with a pre-set separation, and then touch to enable the system. You will be asked to enter the code.

3. WHAT TYPE OF ALARM HAS OCCURRED?

Touch to display the type of alarm that has occurred. The following information will be displayed: type of alarm, zone where the alarm has occurred, date and time.


There are four types of alarms: intrusion, tampering, panic, and technical.


Use to delete all the alarms.

Messages


You can receive and display text messages from the switchboard.


Touch [Functions](#) in the home page and then touch the *Messages* card.


The  icon indicates that new messages have been received.

After the message has been opened, the icon changes status to .

Touch  to delete all messages.



Touch  to delete the displayed message.

Touch  to answer the message from the switchboard.


Energy management

This can be used to check the status of energy loads, display energy consumptions/productions, and monitor the electric system, intervening on Salvavita rearming devices as necessary. Touch [Functions](#) in the home page, and then touch the *Energy management* card.

SYSTEM SUPERVISION


This can be used to display STOP&GO devices and check that the loads of the My Home system are working correctly.

Stop And Go




1. Touch to disable automatic rearming in case of disconnection of the circuit breaker..

Stop And Go Plus



1. Touch to disable automatic rearming in case of disconnection of the circuit breaker.
2. Touch **Open** to force the opening of the circuit breaker; touch **Close** to force its closure.
3. Touch to disable system check. In this way, by touching **Close** it will be possible to force the circuit breaker closed without the need to perform a test.


Stop And Go BTest



1. Touch to disable automatic rearming in case of disconnection of the circuit breaker.
2. Use the **-** **e** **+** to set the frequency of automatic tests (number of days between tests).
3. Touch **Ok** to confirm or **Cancel** to abort.

Load Diagnostic

The "Load Diagnostic" function gives the possibility of checking that the loads are working correctly, by measuring the earth leakage current absorbed by the same.



The ● icon indicates that the load is working correctly; the ● icon indicates that the load is working correctly but the earth leakage current is close to the limits of the standard; the ● icon indicates that the earth leakage current has exceeded the limits of the standard, causing the opening of the Salvavita


CONSUMPTION/PRODUCTION DISPLAY

This can be used to monitor the consumption and the production of energy for: electricity, gas, water, heating/cooling, hot sanitary water.

Global view >	This can be used to display the global goals set by the user using the software, for "Electricity" and "Gas", in a chart or table format.
Electricity >	Display the electric power consumed or produced by the system.
Water >	By connecting a pulse counter to a Water meter with pulse output, it is possible to display the corresponding consumption/production on the system.
Gas >	By connecting a pulse counter to a Gas meter with pulse output, it is possible to display the corresponding consumption on the system.
Hot Water >	By connecting a pulse counter to a Hot Water meter, or to the corresponding pulse output of a heat measurement central unit, found in the apartment user modules (in case of central heating), it is possible to display the corresponding system consumption.
Heating/Cooling >	By connecting the pulse counter to a Heat meter with pulse output it is possible to display the calories/frigorics measured on the Heating/Cooling system (in thermal kWh).

Global view


Global view			
		Value	Unit
		€	
Line	Consumption 01:2013	Goal	Delta
Electricity line 1 ⚡	201,00 kWh	239,00 kWh	- 38,00 kWh
Electricity line 2 ⚡	206,00 kWh	166,00 kWh	+ 40,00 kWh
Electricity line 3 ⚡	65,69 kWh	205,00 kWh	- 139,31 kWh
Electricity line 4 ⚡	122,00 kWh	180,00 kWh	- 58,00 kWh
Electricity line 5 ⚡	240,00 kWh	220,00 kWh	+ 20,00 kWh

Electricity

1. Touch to display electricity consumption/production information.




Warning: This manual only describe the control of Electricity; MyHOME_Screen manages all the energy controls in the same way.




Detailed information


1. Touch a line to display detailed consumption/production information:




2. Touch to toggle between months and days.
3. Indication of the instantaneous consumption.
4. Indication of the total consumption.
5. Touch **Day** or the green line on the chart to display the graphic information split by days; When the line is touched, the center of the display shows a window giving the possibility to select the day to display in chart format.





6. Touch to select the date.
7. Touch to confirm.



Touch  to display the consumption details in a table format:

General

Day Month Year   € kWh < Day 16/01/2013 >


Time	kWh	Time	kWh	Time	kWh
0	0,94	8	1,05	16	0,10
1	1,65	9	1,32	17	0,15
2	1,52	10	0,90	18	0,18
3	0,30	11	0,80	19	0,39
4	0,40	12	0,89	20	0,51
5	0,35	13	1,04	21	0,63
6	0,60	14	1,16	22	0,69
7	0,63	15	0,38	23	0,39

Instant consumption: 1,125 kW

Day cumulative consumption: 16,975 kWh


LOAD MANAGEMENT (WITH LOAD MANAGEMENT CENTRAL UNIT INSTALLED)

The load management central unit gives the possibility of controlling the power engaged, to prevent power disconnection by the meter, excluding loads (like oven, washing machine, microwave, etc.), following the priority level set by the installer.



The ● icon indicates that the load is managed by the load management central unit; icon ○ indicates that the load has been forced and is not managed by the load management central unit; icon ● indicates that the load is disconnected.


1. Touch to access the load management function.
2. Touch the load to display.
3. Touch to force the load; touch icons **-** and **+** to decrease or increase the forcing time (default 2 hours and 30 minutes).



4. Touch to reset the consumption meters.
5. Touch to toggle from kWh to cost display, and vice versa.

LOAD MANAGEMENT (WITHOUT LOAD MANAGEMENT CENTRAL UNIT INSTALLED)

If no load management central unit is installed in the system, and advanced actuators are used, this application gives the possibility of checking the consumption of the loads (e.g. oven, washing machine, microwave oven, etc.).



1. Touch to access the load management function.
2. Touch the load to display.
3. Touch to reset the consumption meters.
4. Touch to toggle from kWh to cost display, and vice versa.


Scenarios

It is possible to enable and modify the scenarios of your My Home system.
Touch [Functions](#) in the Home page and then touch the *Scenarios* card.


SCENARIO OF THE SCENARIO MODULE



To activate a scenario saved in the scenario module touch *Scenario module* and then *Activate* to activate the scenario. If the command is sent successfully, the ✓ symbol appears.





To modify a scenario, or to create a new one, touch  (see [Scenarios > Scenario module](#))

PROGRAMMED SCENARIO




This scenario can be used to send a range a controls following one or more actions occurred at a set time.

It is possible to manage up to 20 of the 300 scenarios configured in the Scenario Programmer.
For this scenario, the four possible actions are:

- Start - Stop  - .
These are sent to force the start and the stop of the scenario, irrespective of the condition programmed.
- Disable scenario - Enable scenario  - .
These can be used to disable / enable the scenario without executing it.
The scenario will be executed when the programmed conditions occur.




MyHOME_Screen SCENARIO




This scenario can be used to send a command at a set time, if a certain condition occurs on a device (e.g. the adjustment level of a dimmer, or the temperature measured by a specific probe).

It is possible to manage up to 20 scenarios.

For this scenario, the two possible actions are:

- Start .
The scenario is executed irrespective of the programmed conditions
- Enable scenario - Disable scenario  - .
This gives the possibility of enabling/disabling the scenario without executing it.
The scenario will be executed when the programmed conditions occur.

To modify the time condition or the condition of the device of the scenario touch  (see [Scenario > MyHOME_Screen scenario](#))

Example of MyHOME_Screen scenario

The watering system comes on in the garden (action)
at 20.30 (time condition)

Legrand SNC
128, av. du Maréchal-de-Lattre-de-Tassigny
87045 Limoges Cedex - France
www.legrand.com

BTicino SpA
Viale Borri, 231
21100 Varese
www.bticino.com